Koala Access Control Panel-MegEye-W3K-45S

The 5-inch version of the intelligent access control device is an infrared binocular 5-inch access control device based on the universal SDK provided by MEGVII. It supports online recognition of 200,000 bases and 20,000 offline recognition. It uses binocular live detection, It is used under complicated light conditions such as low light, backlight, overexposure, etc. It is widely used in office area access control. It can replace the original card swiping point to achieve intelligent identification and identity management.







- > Integrated frontal flat design and full aluminum alloy shell design on the back, high value without losing quality
- > Binocular deep living technology, effective defense against electronic screen and mask attacks
- > 200RGB + 2 million infrared HD camera, 5-inch high-definition touch screen
- > Intelligent face ISP adjustment, intelligent fill light, suitable for a variety of complex light environments such as low light and back light
- ➤ Support 200,000 online 1:N, 20,000 1:N offiline
- > Single recognition <0.5s, making queuing a past tense
- > Support swipe down the screen, enjoy the honor
- > Support wall mounted installation

Product Specification:

Category	Parameters	
Dimension	Length*Width*Thickness146*74*20	
Chips	Baseband	SnapDragon 450 8Core 1.8G
Memory	RAM	2GB
	ROM	16GB
0S		Android 8.1
Display	Dimension	5 Inch (MIPI) IPS

	Resolution	720*1280
	Lux	450 Cd/m2
Touch Screen	Туре	capacitive
100011 001 0011	Touch Points	5
	Response Time	
	Transmittance	<u> </u>
	Surface	6H
	hardness	ОП
 Camera	Pixels	2M
oamor a	FocalLenght	1. 5mm
	Field of View	117°
	IR Camera	
Damar Committee		Equipped
Power Supply	DC Powered	12V 2A
Audio	SPK	8Ω 1W
Supported	Video	1080p 60fps
Format	Audio	(H. 264/H265/VP8/VP9)
		MD4. COODING CAVI. VMD-NR
	Audio	MP3; aacPlus, eAAC; AMR-NB, AMR-WB, G.711, WMA9/10 Pro
Port	WIFI	
Port		AMR-WB, G.711, WMA9/10 Pro
Port	WIFI	AMR-WB, G.711, WMA9/10 Pro 2.4G 802.11 b/g/n
Port	WIFI 485	AMR-WB, G.711, WMA9/10 Pro 2.4G 802.11 b/g/n x1
Port	WIFI 485 Wiegand	AMR-WB, G. 711, WMA9/10 Pro 2. 4G 802. 11 b/g/n x1 x1
Port	WIFI 485 Wiegand LAN	AMR-WB, G. 711, WMA9/10 Pro 2. 4G 802. 11 b/g/n x1 x1 X1 (10M/100M)
Port	WIFI 485 Wiegand LAN Door Button	AMR-WB, G. 711, WMA9/10 Pro 2. 4G 802. 11 b/g/n x1 x1 X1 (10M/100M) X1
Port IC Card	WIFI 485 Wiegand LAN Door Button Relay	AMR-WB, G. 711, WMA9/10 Pro 2. 4G 802. 11 b/g/n x1 x1 X1 (10M/100M) X1 X1
	WIFI 485 Wiegand LAN Door Button Relay Tamper	AMR-WB, G. 711, WMA9/10 Pro 2. 4G 802. 11 b/g/n x1 x1 X1 (10M/100M) X1 X1 X1 X1
IC Card	WIFI 485 Wiegand LAN Door Button Relay Tamper Frequency	AMR-WB, G. 711, WMA9/10 Pro 2. 4G 802. 11 b/g/n x1 x1 X1 (10M/100M) X1 X1 X1 X1 X1 X1 X1 X1
IC Card	WIFI 485 Wiegand LAN Door Button Relay Tamper Frequency Card Type	AMR-WB, G. 711, WMA9/10 Pro 2. 4G 802. 11 b/g/n x1 x1 X1 (10M/100M) X1 X1 X1 X1 X1 M1/CPU
IC Card Reader	WIFI 485 Wiegand LAN Door Button Relay Tamper Frequency Card Type Read Speed	AMR-WB, G. 711, WMA9/10 Pro 2. 4G 802. 11 b/g/n x1 x1 X1 (10M/100M) X1 X1 X1 X1 X1 One of the second sec
IC Card Reader	WIFI 485 Wiegand LAN Door Button Relay Tamper Frequency Card Type Read Speed Online Base	AMR-WB, G. 711, WMA9/10 Pro 2. 4G 802. 11 b/g/n x1 x1 X1 (10M/100M) X1 X1 X1 X1 AND X1 X1 X1 X1 X1 X1 X1 X1 X1 X
IC Card Reader	WIFI 485 Wiegand LAN Door Button Relay Tamper Frequency Card Type Read Speed Online Base Offline Base	AMR-WB, G. 711, WMA9/10 Pro 2. 4G 802. 11 b/g/n x1 x1 X1 (10M/100M) X1 X1 X1 X1 X1 One of the second sec